## Residual Current Device (RCD) - Portable (ALL)

Last Issue Date: 27/03/2017 Activity		Type Of Service				
		Α	В	С	D	Е
1	Undertake the Push-button test to ensure correct operation. If the RCD fails to trip it must be replaced.			Y	Υ	Y
2	Undertake an external inspection. Check for damage, defects or modifications and for discolouration. Also check the condition of the flexible lead, plug top and the terminals.				Y	Y
3	Check all connections at the RCD.				Y	Υ
4	Check the continuity of the protective earth conductors in accordance with AS3760, Section 2.3.3.1 and Appendix D.				Y	Y
5	Test the insulation in accordance with AS3760, Section 2.3.3.2 and Appendix E.				Υ	Υ
6	Testing of operation of RCDs is to be done in accordance with AS3760, section 2.3.3.4 and Appendix H. Ensure tripping times comply with the requirements set out in the tables. Non-compliant RCDs are to be withdrawn from use and followed with remedial, replacement or other corrective action.				Y	Y
7	Compliant RCDs are to be tagged, information to include:  (a) Name of test person / company;  (b) Test or inspection date, the re-test date and reference to AS3760.				Υ	Y
8	Record the following information in the log book:  a) Identification of the RCD/Circuit ID number; b) The date the test was carried out; c) The date for the next test: d) The name and company of the person who undertook the test; e) The outcome of the test including the RCD tripping times and a description of any defects and repairs carried out.			Y	Y	Y

**Disclaimer -**This TDS is intended to provide <u>guidance only</u> to support Preventative Maintenance servicing activities. All TDS users are encouraged to read and understand the full <u>Conditions of Use</u> provided on the final page of this document and on the DPTI website.

Government of South Australia

Department of Planning,
Transport and Infrastructure

For more information please contact the applicable Facilities Management Service Provider.

## **Special Comments and Technical Data**

UNDERTAKE THE FULL INSPECTION (BOTH VISUAL AND PHYSICAL) AND

TESTING OF THE RCD IN ACCORDANCE WITH AS3760. FOR

INSPECTION AND TESTS REFER TO SECTION 2 AND APPENDIX H.

SERVICING FREQUENCIES TO BE DETERMINED BY THE TYPE OF

ENVIRONMENT AND HOW THE EQUIPMENT IS USED.

FOR RESIDENTIAL TYPE AREAS OF HOTELS, BOARDING HOUSES, HOSTEL

ACCOMMODATION, RESIDENTIAL INSTITUTIONS, HOUSES ETC REQUIRED REOUIRED SERVICES ARE:

C SERVICE - 6 MONTHLY (BY USER / SITE IF REQUESTED)

E SERVICE - 2 YEARLY

FOR A NON 'HOSTILE' ENVIRONMENT REQUIRED SERVICES ARE:

C SERVICE - 3 MONTHLY (BY USER / SITE IF REQUESTED)

E SERVICE - 2 YEARLY (NOTE THE D SERVICE IS NOT DONE)

FOR `HOSTILE' ENVIRONMENTS REQUIRED SERVICES ARE:

C SERVICE - 3 MONTHLY (BY USER / SITE IF REQUESTED)

D SERVICE - ANNUALLY

FOR FACTORIES; PLACES OF MANUFACTURE, MAINTENANCE ETC

REQUIRED SERVICES ARE:

C SERVICE - DAILY OR BEFORE EVERY USE, WHICHEVER IS THE

LONGER (BY USER / SITE IF REQUESTED)

D SERVICE - ANNUALLY

FOR EQUIPMENT TYPES: COMMERCIAL CLEANING; HIRE; AND REPAIRED

SERVICED AND SECOND-HAND REFER TO TABLE 4, AS3760. NOTE: THE SCOPE OF THE D AND E SERVICE IS IDENTICAL.

**Disclaimer** -This TDS is intended to provide <u>guidance only</u> to support Preventative Maintenance servicing activities. All TDS users are encouraged to read and understand the full <u>Conditions of Use</u> provided on the final page of this document and on the DPTI website.



For more information please contact the applicable Facilities Management Service Provider.

**Download Date:** 22/12/2020 2 of 3

## **Conditions of Use**

A TDS should be used as a generic guide for Facilities Management Service Providers (FMSP) to deliver Facilities Maintenance Services, specifically Preventative Maintenance in accordance with the DPTI *Agency Work Procedure Manual*.

Users of a TDS should familiarise themselves with the following Conditions of Use:

- 1. You use the information and data contained in any TDS published by DPTI at your sole risk. DPTI-AGFMA does not have the expertise to provide complete or accurate technical data schedules and provides these technical data sheets merely as a starting point and/or guide.
- If you rely on the information in a TDS you are responsible for ensuring, by independent verification, its accuracy, currency and completeness. DPTI cannot guarantee that the information contained in a TDS meets the standards or requirements of legislative requirements.
- 3. A TDS is not an exhaustive list of tasks or obligations that may be required and is generally generic in nature. DPTI does not oblige the user of a TDS to rely on it to the exclusion of other sources of information. For example, manufacturer's requirements may need to be followed for additional and / or alternative tasks and for additional and / or alternative servicing frequencies. You should always check the primary source of information such as the Australian Standards, manufacturer's specifications, legislation and other standards before undertaking any work to which a schedule may apply.
- You must apply appropriate risk management principles and carry out all tasks in accordance with obligations under the <u>Work Health and Safety Act 2012.</u>
- 5. You must not use a TDS unless you meet the specific competency requirements for preventative maintenance servicing works and are capable of applying the TDS to your trade or area of expertise. A TDS is only to be used by people who are specifically instructed by DPTI to use them and only for work undertaken in South Australia.
- 6. DPTI, its agents, instrumentalities, officers and employees make no representations, express or implied, as to the accuracy of the information, the data contained in a TDS or the suitability of a TDS for a particular purpose.
- 7. DPTI does not provide legal advice. DPTI accepts no liability, howsoever arising, for any loss resulting from the use of a TDS and any information or data or reliance placed on them.
- 8. DPTI may change information and data in a TDS without notice.
- 9. DPTI may revise this disclaimer at any time by updating these Conditions of Use.



**Download Date: 22/12/2020** 

3 of 3